



855 Purchase Order Acknowledgment

X12/V4010/855: 855 Purchase Order Acknowledgment

Version: 1.0 Final

Author:	Seagate B2B
Publication:	
Trading Partner:	
Notes:	Ansi X12 EDI 855 to be used with OEM, Distribution or Retail partners.

Table of Contents

855	Purchase Order Acknowledgment	3
ISA	Interchange Control Header	4
GS	Functional Group Header	6
ST	Transaction Set Header	8
BAK	Beginning Segment for Purchase Order Acknowledgment	9
PO1	Loop PO1	10
PO1	Baseline Item Data	11
ACK	Loop ACK	13
ACK	Line Item Acknowledgment	14
CTT	Loop CTT	16
CTT	Transaction Totals	17
SE	Transaction Set Trailer	18
GE	Functional Group Trailer	19
IEA	Interchange Control Trailer	20

855

Purchase Order Acknowledgment

Functional Group=PR

Purpose: This Draft Standard for Trial Use contains the format and establishes the data contents of the Purchase Order Acknowledgment Transaction Set (855) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to a seller's acknowledgment of a buyer's purchase order. This transaction set can also be used as notification of a vendor generated order. This usage advises a buyer that a vendor has or will ship merchandise as prearranged in their partnership.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>	<u>Page</u>
	ISA	Interchange Control Header	M	1			Must use	4
	GS	Functional Group Header	M	1			Must use	6

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>	<u>Page</u>
010	ST	Transaction Set Header	M	1			Must use	8
020	BAK	Beginning Segment for Purchase Order Acknowledgment	M	1			Must use	9

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>	<u>Page</u>
LOOP ID - PO1					100000	N2/010L		10
010	PO1	Baseline Item Data	O	1		N2/010	Used	11
LOOP ID - ACK					104			13
270	ACK	Line Item Acknowledgment	O	1			Used	14

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>	<u>Page</u>
LOOP ID - CTT					1	N3/010L		16
010	CTT	Transaction Totals	O	1		N3/010	Used	17
030	SE	Transaction Set Trailer	M	1			Must use	18

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>	<u>Page</u>
	GE	Functional Group Trailer	M	1			Must use	19
	IEA	Interchange Control Trailer	M	1			Must use	20

Notes:

2/010L PO102 is required.

2/010 PO102 is required.

3/010L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/010 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use
Description: Code to identify the type of information in the Authorization Information						
		<u>Code</u>	<u>Name</u>			
		00	No Authorization Information Present (No Meaningful Information in I02)			
ISA02	I02	Authorization Information	M	AN	10/10	Must use
Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)						
ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use
Description: Code to identify the type of information in the Security Information						
		<u>Code</u>	<u>Name</u>			
		00	No Security Information Present (No Meaningful Information in I04)			
ISA04	I04	Security Information	M	AN	10/10	Must use
Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)						
ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified						
ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use
Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element						
User Note 1: Seagate Production ISA ID: 098533326						
Seagate Test ISA ID: 098533326TST						
ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified						
		<u>Code</u>	<u>Name</u>			
		01	Duns (Dun & Bradstreet)			
ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use
Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them						
ISA09	I08	Interchange Date	M	DT	6/6	Must use
Description: Date of the interchange						
ISA10	I09	Interchange Time	M	TM	4/4	Must use
Description: Time of the interchange						

ISA11	I10	Interchange Control Standards Identifier	M	ID	1/1	Must use
Description: Code to identify the agency responsible for the control standard used by the message that is enclosed by the interchange header and trailer						
		<u>Code</u>	<u>Name</u>			
		U	U.S. EDI Community of ASC X12, TDCC, and UCS			
ISA12	I11	Interchange Control Version Number	M	ID	5/5	Must use
Description: Code specifying the version number of the interchange control segments						
		<u>Code</u>	<u>Name</u>			
		00400	Standard Issued as ANSI X12.5-1997			
ISA13	I12	Interchange Control Number	M	N0	9/9	Must use
Description: A control number assigned by the interchange sender						
ISA14	I13	Acknowledgment Requested	M	ID	1/1	Must use
Description: Code sent by the sender to request an interchange acknowledgment (TA1)						
		<u>Code</u>	<u>Name</u>			
		0	No Acknowledgment Requested			
ISA15	I14	Usage Indicator	M	ID	1/1	Must use
Description: Code to indicate whether data enclosed by this interchange envelope is test, production or information						
		<u>Code</u>	<u>Name</u>			
		P	Production Data			
ISA16	I15	Component Element Separator	M		1/1	Must use
Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator						

User Note 1:

Sample Data: ISA*00* *00*
 *01*XXXXXXXXXXXXXXXXXX*01*098533326
 *100215*0730*U*00400*000001432*0*P*|~

GS**Functional Group Header**

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use**Purpose:** To indicate the beginning of a functional group and to provide control information**Element Summary:**

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use
		Description: Code identifying a group of application related transaction sets				
		<u>Code</u>		<u>Name</u>		
		PR		Purchase Order Acknowledgement (855)		
GS02	142	Application Sender's Code	M	AN	2/15	Must use
		Description: Code identifying party sending transmission; codes agreed to by trading partners				
		User Note 1: Seagate Production GS ID: 098533326				
		Seagate Test GS ID: 098533326TST				
GS03	124	Application Receiver's Code	M	AN	2/15	Must use
		Description: Code identifying party receiving transmission; codes agreed to by trading partners				
GS04	373	Date	M	DT	8/8	Must use
		Description: Date expressed as CCYYMMDD				
GS05	337	Time	M	TM	4/8	Must use
		Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)				
GS06	28	Group Control Number	M	N0	1/9	Must use
		Description: Assigned number originated and maintained by the sender				
GS07	455	Responsible Agency Code	M	ID	1/2	Must use
		Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480				
		<u>Code</u>		<u>Name</u>		
		X		Accredited Standards Committee X12		
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use
		Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed				
		<u>Code</u>		<u>Name</u>		
		004010		Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1997		

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

- 1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

User Note 1:

Sample Data:

GS*PR*XXXXXXXXXXXXXXXX*098533326*100215*0730*1433*X*004010~

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use

Description: Code uniquely identifying a Transaction Set

Record Name: Header Position 123

Example: transaction_type

<u>Code</u>	<u>Name</u>
855	Purchase Order Acknowledgment

ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

User Note 1:

Sample Data: ST*855*1~

BAK Beginning Segment for Purchase Order Acknowledgment

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Acknowledgment Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BAK01	353	Transaction Set Purpose Code	M	ID	2/2	Must use
		Description: Code identifying purpose of transaction set				
		<u>Code</u>		<u>Name</u>		
		00		Original		
BAK02	587	Acknowledgment Type	M	ID	2/2	Must use
		Description: Code specifying the type of acknowledgment				
		<u>Code</u>		<u>Name</u>		
		AC		Acknowledge - With Detail and Change		
		AD		Acknowledge - With Detail, No Change		
BAK03	324	Purchase Order Number	M	AN	1/22	Must use
		Description: Identifying number for Purchase Order assigned by the orderer/purchaser				
BAK04	373	Date	M	DT	8/8	Must use
		Description: Date expressed as CCYYMMDD				

Semantics:

1. BAK04 is the date assigned by the purchaser to purchase order.
2. BAK08 is the seller's order number.
3. BAK09 is the date assigned by the sender to the acknowledgment.

User Note 1:

Sample Data: BAK*00*AC*PO5567210*100210~

Loop PO1

Pos: 010	Repeat: 100000
Optional	
Loop: PO1	Elements: N/A

User Option (Usage): Used

Purpose: To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	PO1	Baseline Item Data	O	1		Used
270		Loop ACK	O		104	Used

PO1 Baseline Item Data

Pos: 010	Max: 1
Detail - Optional	
Loop: PO1	Elements: 6

User Option (Usage): Used

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	O	AN	1/20	Used
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
PO102	330	Quantity Ordered	X	R	1/15	Used
		Description: Quantity ordered				
PO103	355	Unit or Basis for Measurement Code	O	ID	2/2	Used
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		<u>Code</u>		<u>Name</u>		
		EA		Each		
PO104	212	Unit Price	X	R	1/17	Used
		Description: Price per unit of product, service, commodity, etc.				
PO106	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<u>Code</u>		<u>Name</u>		
		BP		Buyer's Part Number		
PO107	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

User Note 1:

Sample Data: PO1*1*230*EA*75**BP*674331-01~

Loop ACK

Pos: 270	Repeat: 104
Optional	
Loop: ACK	Elements: N/A

User Option (Usage): Used

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
270	ACK	Line Item Acknowledgment	O	1		Used

ACK Line Item Acknowledgment

Pos: 270	Max: 1
Detail - Optional	
Loop: ACK	Elements: 5

User Option (Usage): Used

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ACK01	668	Line Item Status Code	M	ID	2/2	Must use

Description: Code specifying the action taken by the seller on a line item requested by the buyer

<u>Code</u>	<u>Name</u>
DR	Item Accepted - Date Rescheduled
IA	Item Accepted
IC	Item Accepted - Changes Made
ID	Item Deleted
IQ	Item Accepted - Quantity Changed

ACK02	380	Quantity	X	R	1/15	Used
-------	-----	----------	---	---	------	------

Description: Numeric value of quantity

ACK03	355	Unit or Basis for Measurement Code	X	ID	2/2	Used
-------	-----	------------------------------------	---	----	-----	------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

<u>Code</u>	<u>Name</u>
EA	Each

ACK04	374	Date/Time Qualifier	O	ID	3/3	Used
-------	-----	---------------------	---	----	-----	------

Description: Code specifying type of date or time, or both date and time

<u>Code</u>	<u>Name</u>
017	Estimated Delivery
068	Current Schedule Ship

ACK05	373	Date	X	DT	8/8	Used
-------	-----	------	---	----	-----	------

Description: Date expressed as CCYYMMDD

Syntax Rules:

1. P0203 - If either ACK02 or ACK03 is present, then the other is required.
2. C0405 - If ACK04 is present, then ACK05 is required.
3. P0708 - If either ACK07 or ACK08 is present, then the other is required.
4. P0910 - If either ACK09 or ACK10 is present, then the other is required.
5. P1112 - If either ACK11 or ACK12 is present, then the other is required.
6. P1314 - If either ACK13 or ACK14 is present, then the other is required.
7. P1516 - If either ACK15 or ACK16 is present, then the other is required.
8. P1718 - If either ACK17 or ACK18 is present, then the other is required.
9. P1920 - If either ACK19 or ACK20 is present, then the other is required.
10. P2122 - If either ACK21 or ACK22 is present, then the other is required.
11. P2324 - If either ACK23 or ACK24 is present, then the other is required.
12. P2526 - If either ACK25 or ACK26 is present, then the other is required.
13. P2728 - If either ACK27 or ACK28 is present, then the other is required.
14. C282729 - If ACK28 is present, then ACK27 and ACK29 are required.

Semantics:

1. ACK29 Industry Reason Code may be used to identify the item status. In addition, it may be used in conjunction with ACK01 to further clarify the status.

User Note 1:

Sample Data: *ACK*DR*25*EA*017*100325~*

Loop CTT

Pos: 010	Repeat: 1
Optional	
Loop: CTT	Elements: N/A

User Option (Usage): Used

Purpose: To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	CTT	Transaction Totals	0	1		Used

CTT Transaction Totals

Pos: 010	Max: 1
Summary - Optional	
Loop: CTT	Elements: 1

User Option (Usage): Used

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

Description: Total number of line items in the transaction set

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

User Note 1:

Sample Data: CTT*1~

SE Transaction Set Trailer

Pos: 030	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use

Description: Total number of segments included in a transaction set including ST and SE segments

SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	---------------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Comments:

1. SE is the last segment of each transaction set.

User Note 1:

Sample Data: SE*7*1~

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	N0	1/6	Must use
Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element						
GE02	28	Group Control Number	M	N0	1/9	Must use
Description: Assigned number originated and maintained by the sender						

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

User Note 1:

Sample Data: GE*1*1433~

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups	M	N0	1/5	Must use
		Description: A count of the number of functional groups included in an interchange				
IEA02	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				

User Note 1:

Sample Data: IEA*1*000001432~